At SEA.AI, we are committed to providing our users with the best possible experience by regularly releasing software updates. These updates include the latest technological advancements, enhancements to existing features, and critical bug fixes. This document provides information and step-by-step instructions for updating your Sailing software to 7.3.0 version.

Option 1: Update Automatically

- The new application version 7.3.0 will be available for download from the Apple Store at the end of September 2024.
- After downloading the app, you will receive a prompt to automatically update your system.

Option 2: Manual Update (Immediate)

To perform an immediate update, follow these steps:

1. **Find the IP Address:**
    - Locate the IP address assigned to SEA.AI by checking the network settings on your MFD (Raymarine/Garmin) diagnostic page.
    - Alternatively, you can follow this video guide for assistance.
2. **Connect to MFD Wi-Fi:**
    - Use a phone, tablet, or computer to connect to the MFD's Wi-Fi network.
3. **Download the Update File:**
    - On your device, download the update file: SEA-AI_Sailing_7.3.0.oscar.
4. **Access the Update Interface:**
    - With your device connected to the MFD Wi-Fi, open a web browser (e.g., Chrome) and enter the following URL: http://XXX.XXX.XXX.XXX/WebContent/page/welcome.html (replace XXX.XXX.XXX.XXX with the IP address found in Step 1, 192.168.1.191 for example).
5. **Upload the Update:**
    - On the web interface, navigate to Settings › System › Update and upload the update file you downloaded.

Note: If you choose to update manually, you may see a notification about 'incompatibility' until the new app is officially released. Just ignore it as it will not affect your system's performance.

The information contained in this document is proprietary to SEA.AI GmbH and is to be used only for the purpose for which it is supplied. It shall not be disclosed, in whole or in part, to any other party without the expressed written permission of SEA.AI GmbH.

For B&G MFD Users:

1. **Find the IP Address:**
    - As with the standard update process, locate the IP address assigned to SEA.AI through the network settings on your B&G MFD.
    - Refer to this video guide if needed.
2. **Connect to Router:**
    - Connect your phone, tablet, or computer to a router that is connected between the SEA.AI system and the B&G screens. This router is required for the update process.

Note: This update is the final one available for Advanced systems manufactured before 2021. For more information, please contact your sales representative.

The information contained in this document is proprietary to SEA.AI GmbH and is to be used only for the purpose for which it is supplied. It shall not be disclosed, in whole or in part, to any other party without the expressed written permission of SEA.AI GmbH.